

PROCEDIMIENTO PARA ACTUALIZACIÓN DE FIRMWARE DE LA CÁMARA IDS-
TCM203-A/0832

Observación: La actualización debe realizarse en 2 pasos

PASO 1

- 1- Ingresar a Device Configuration/System Maintenance/
- 2- En Configuration File elegis el archivo alg.img
- 3- Darle click al botón IMPORT

The screenshot shows a web interface with several sections:

- Default**: Contains two buttons: "Soft Reset" (Reset all the parameters, except the IP parameters and user information, to the default settings.) and "Hard Reset" (Restore the device to the factory default status.).
- Debug File Export**: Contains a "Debug File Export" button.
- Export Configuration File**: Contains an "Export" button.
- Import Configuration File**: Contains a dropdown menu for "Importing Method" (set to "Import All"), a text input for "Configuration File" (containing "C:\fw\alg.img"), and "Browse" and "Import" buttons. The "Status" field is empty.
- Upgrade**: Contains a text input for "Upgrading File", "Browse" and "Upgrade" buttons. The "Status" field is empty.

Note : The upgrading may take 1 to 10 minutes. Please do not power off the device during upgrading.

PASO 2

- 4- En UPGRADING FILE elegís el archivo digicap.dav
- 5- Darle click al botón UPGRADE.
- 6- Reiniciar el equipo

The screenshot shows the same web interface as in Step 1, but with the following changes:

- The **Export Configuration File** section is visible at the top.
- The **Import Configuration File** section is visible below it, with the same settings as in Step 1.
- The **Upgrade** section is now active. The "Upgrading File" text input contains "C:\fw\digicap.dav". The "Browse" and "Upgrade" buttons are visible. The "Status" field is empty.

Note : The upgrading may take 1 to 10 minutes. Please do not power off the device during upgrading.

Observación: Chequear si los firmwares coinciden con esta imagen:

Basic Information	
Device Name	IP CAPTURE CAMERA
Device No.	88
Model	iDS-TCM203-A
Serial No.	iDS-TCM203-A 20210409AIF81672278
Firmware Version	V4.2.5 201202
Encoding Version	V4.0 build 191114
Hardware Version	0x433900
Number of Channels	1
Number of Trigger Input	2
Number of Trigger Output	2
Smart Module Status	normal__3__ma start ok
Algorithms Library Version	
ALG	v2.2.0 build20201202
LPR	13.0.2 20-11-30
VCR	0.0.0 00-00-00
VTR	9.0.0 18-04-23
ISP	1.2.1 18-11-27
AEC	2.6.7 17-11-13
AWB	2.4.2 17-2-23
DSP	4.0.0 19-11-14
BSP	v2.0.34326
VSD	0.0.0 00-00-00
VSF	0.0.0 00-00-00
VFR	9.0.2 18-04-23
VTS	2.2.2 18-10-26